

VoiceLink III IR-255



Two channel infrared receiver and power supply

Specifications

Receiver Input	Infrared FM
Modulation	FM Wide-band
Reception Frequencies	Ch. A: 2.08 MHz Ch. B: 2.54 MHz
Infrared Wavelength	850 nm
Tone Signal	Ch. A: 32.768 KHz
De-emphasis	50 μ s
Frequency Response	40 Hz, -18KHz, \pm 3dB
S/N Ratio	>65 dB
THD	<1% @1KHz
Nominal Deviation	\pm 10 KHz
Maximum Deviation	\pm 25 KHz
External Sensor Input	Two, RCA
Connectivity Coverage	1,600 Sq. Ft.
Line Input	Computer/Aux 3.5mm front or Dual RCA input rear panel
Line Output	Balanced Line, Three Pin Phoenix connector Unbalanced Line, 1/4" Phone Lesson Capture with level control 3.5mm front panel
Power Supply	12VDC / 0.6A / 7.2W
Dimensions	8 3/8" W x 1 3/4" H x 7" D
Weight	1lbs. 7 oz.

Features

- Two infrared wireless microphone receivers
- One Line Level Computer/Aux input 3.5mm front or Dual RCA inputs rear panel
- Lesson Capture output with level control on front panel (3.5mm)
- Balanced line output 3-pin phoenix connector
- Unbalanced output, 1/4" phone, line level
- Two external sensor inputs for ultimate coverage
- Rack mountable with rack mount kit (RM-268)